

Professional Equalizer

GRAPHIC EQUALIZER



PRODUCT

EQ-1530

EQ-1030

EQ-152

EQ-321

Specification
User Manual

กราฟฟิคอีควอไลเซอร์

ผลิตในประเทศไทย

SPECIFICATION : EQ-312, EQ-1030, EQ-1520T, EQ-321

	EQ-312	EQ-1030	EQ-152	EQ-1530
Type	Stereo Graphic Equalizer	Graphic Equalizer	Graphic Equalizer	Graphic Equalizer
Frequency Response	+0db-3db 5Hz.-20kHz.	+3db-3db 20Hz.-20kHz.	+0db-3db 5Hz.-20kHz.	+0db-3db 5Hz.-20kHz.
Gain	0 - +15 -15dB.	0 dB.	0 - +15 -15dB.	0 - +15 -15dB.
Total Harmonic Distortion	Less than 0.1%, 20 Hz.-20 kHz.	Less than 0.1%, 20 Hz.-20 kHz.	Less than 0.1%, 20 Hz.-20 kHz.	Less than 0.1%, 20 Hz.-20 kHz.
Output Level Maximum	5 volts 1kHz.20k Ohms.	5 volts 1kHz.20k Ohms.	5 volts 1kHz.20k Ohms.	5 volts 1kHz.20k Ohms.
Frequency Center	20,25,31.5,40,50,63,80,100,125, 160,200,250,315,400,500,630,800, 1k,1.25k,1.6k,2k,2.5k,3.15k,4k,5k, 6.3k,8k,10k,12.5k,16k,20k,HZ.	32,64,125,250,500,1K, 2K,4K,8K,16K, Hz.	25,40,63,100,160,250,400,630, 1k,1.6k,2.5k,4k,6.3k,10k,16k, Hz.	25,40,63,100,160,250,400,630, 1k,1.6k,2.5k,4k,6.3k,10k,16k,HZ.
Range of boost	0 - -15db; +15db.	0 - -15db; +15db.	0 - -15db; +15db.	0 - -15db; +15db.
Input Impedance	20K Ohms. balance & unbalance	22K Ohms. unbalance	20K Ohms. balance & unbalance	20K Ohms. balance & unbalance
Output Impedance	600 Ohms. balance & unbalance	600 Ohms. unbalance	600 Ohms. balance & unbalance	600 Ohms. balance & unbalance
Selector	By Pass or Equalizer	By Pass or Equalizer	By Pass or Equalizer	By Pass or Equalizer
Power Requirement	220VAC.,50/60 Hz.	220VAC.,50/60 Hz.	220VAC.,50/60 Hz.	220VAC.,50/60Hz. High Pass Filter40.Hz.
LED Indicator	ON-OFF Power 220 V.AC.	ON-OFF Power 220 V.AC.	ON-OFF Power 220 V.AC.	ON-OFF Power 220 V.AC.
Dimension (WxHxD)	483 x 95 x 155 mm.	483 x 62 x 165 mm.	483 x 50 x 165 mm.	483 x 62 x 165 mm.
Net Weight	2.1 Kg.	1.3 Kg.	1.1 Kg.	1.9 Kg

Note : Specification and design subject Modification without notice

หาซื้อได้ตามร้านเครื่องเสียงชั้นนำทั่วประเทศ

