

PA Amplifier with USB/SD & FM & Blue Tooth

EA-30 (30W), EA-60 (60W), EA-120 (120W)

Features:

- ✓ Compact mini size public address amplifier
- ✓ Ideal for classroom sound system use
- ✓ Built-in 100V/70V transformer technology
- ✓ Tabletop amplifier with Mp3 player, FM radio & blue tooth
- ✓ Rate power output at 30W, 60W to 120W.
- ✓ Speaker output of 100V or 70V & 4Ohms-8 Ohms-16 Ohms
- ✓ Mp3 player with USB/SD input on front panel, IR remote control for Mp3 player, FM radio and blue tooth
- ✓ LED indicators for power, clip, protect and signal
- ✓ Mic1-3 and line 1-2 and telephone input. Mic1 of balanced XLR input with phantom power on rear panel. Mic2-3 microphone or line switchable unbalanced 6.3mm phone jack input. Line 1-2 input of RCA input and one RCA line output. Telephone input with VOX priority and MOH (Music on Hold).
- ✓ Volume control for Mic1-3, line1-2, Mp3/FM, bass/treble and master
- ✓ With short-circuit, clip, overload and high temp protection
- ✓ AC220V or 115V & 24V DC both operation system



Specification:

Model	EA-30	EA-60	EA-120
Description	PA Amplifier with USB/SD & FM & Blue Tooth		
Rated Power Output	30W	60W	120W
Speaker Outputs	100V or 70V & 4Ohms-8 Ohms-16 Ohms		
Connector	Mic1 input by balanced XLR with phantom power Input2-3 inputs Mic/Line switchable unbalanced 6.3mm phone jack Line1-2 inputs by RCA; Line output by RCA		
Attenuation	Microphone1-3, line1-2 and Mp3/FM, bass/treble and master		
Input	MIC1-3: 5-8mV, 600 Ω ; Line, 150-470mV, 10K Ω , unbalanced RCA		
Line Out	0.775(0dBV)		
Frequency Response	60Hz-15kHz(± 3 dB)		
S/N Ratio	Line ≥ 85 dB, Mic ≥ 72 dB		
THD	Less than 0.5%		
Protection	short-circuit, clip, overload and high temp protection		
Power Consumption	60W	100W	200W
Power Supply	AC220V or 115V & 24V DC /50-60Hz		
Dimension	300(W) \times 275(D) \times 88(H)mm		
Weight	3kg	6.7kg	7.8kg

Rear Panel:

