

**FU-831 Series**

**New**

**FU-831/MT-831/MT-831**



ไมโครโฟนไร้สายปรับความถี่ได้

มีทั้งแบบไมค์ดัดดูแผล:  
แบบไมค์ดัดดู+Headset

**FU-831/MT-831/MH-832**



Specification : **FU-831**

**System**

Frequency range: 710-830 MHz.  
Band width: <200 KHz.  
Frequency response: 35Hz.-20KHz.  
Dynamicrange: >100dB  
T.H.D.:<0.5%  
S/N ratio: >90dB  
Valid distance: >50m

**Transmitter**

Transmitter: 10mW  
Oscillation mode: PLL  
Adjustment mode: FM  
Image controlment: >50dB  
Adjust Frequency deviation:<75KHz.  
Channel Switch mode: Coding Swich  
Power:DC 2.4-3.6V(AA battery 1.5Vx2)

**Receiver**

Sensitivity: 2.0 u V  
Oscillation mode: PLL  
S/N Ration: >90dB  
Distortion: <0.5%  
Channel switch mode :  
microcomputercontrolment button  
Output: balanced output x2,  
6.35 mixing output x1  
Power: AC220V; DC 16-20V

\* Specifications are subject to change without prior notice

