

PROFESSIONAL DIGITAL PRODUCTS

MODEL:EQ-231 STEREO GRAPHIC EQUALIZER 31 BAND

ผลิตในประเทศไทย

Made In Thailand



SPECIFICATION : EQ-231

Type.....	Stereo Graphic Equalizer
Frequency Response.....	+0db—3db 5Hz.-20kHz.
Gain.....	0- + 15 - 15dB.
Total Harmonic Distortion.....	Less than 0.1 %, 20Hz. - 20kHz.
Output level Maximum.....	.5 volts 1khz.20k Ohms.
Frequency Center.....	20, 25, 31.5, 40, 50, 63, 80, 100, 125, 160, 200, 250, 315, 400, 500, 630, 800, 1k, 1.25k, 1.6k, 2k, 2.5k, 3.15k, 4k, 5k, 6.3k, 8k, 10k, 12.5k, 16k, 20k, Hz.
Range of boost.....	0 - - 15db; + 15db.
Input Impedance.....	20K Ohms. balance & unbalance.
Output Impedance.....	600 Ohms. balance & unbalance.
Selector.....	By pass or Equalizer
Power Requirement.....	220 VAC., 50/60 Hz.
LED Indicator.....	ON - OFF Power 220V.AC
Dimension (WxHxD).....	483x95x155 mm.
Net Weight.....	2.1 Kg.

Note : Specification and design subject Modification without notice

