

# Voice Alarm Remote Microphone (Touch Screen) EVAC-500TM

## Features:

- ✓ Digital voice evacuation system remote paging microphone.
- ✓ Each microphone of 120 zone capacity.
- ✓ Support 32 remote microphones of loop connection.
- ✓ Remote paging microphone with touch screen display.
- ✓ System indicators of AC, DC, fault, Mic status and test.
- ✓ 120 zone selection buttons through touch screen and all zone/talk button.
- ✓ Two RJ45 ports for connection with EVAC-500 and next remote microphone.
- ✓ One 3.5mm line input, with output volume control.
- ✓ Support PPT and normal paging two modes.
- ✓ DC24V power supply or POE.
- ✓ Support loop connection and paging microphone failure has been supervised.
- ✓ With free software to monitor the microphone working status and fault.



## Specifications:

Model	EVAC-500TM
Description	Voice Alarm Remote Microphone (Touch Screen)
Power Consumption	3W
Zone Capacity	120 Zones
System Capacity	32 Remote microphones
Line Inputs	350mV, 10kΩ
Mic Input	5mV, 600Ω
Frequency Response	80Hz~16kHz
THD	<1% at RMS,1KHz
S/N Ratio	>70dB
Operating Temp	-20℃ to +70℃
Power Supply	DC24V, ±20%
Humidity	<95% no condensation
Dimension	256(W)×149(H)×52(D) mm
Weight	1.5kg

## Connection:

